



## Three-phase motorstarter 400 V with emergency stop button

|               |                         |
|---------------|-------------------------|
| Manufacturer: | Klinger & Born          |
| Type:         | K3000/3Ph-400/Not-Aus/P |
| Product no.:  | 0099.3002               |
| Weight:       | 1.600                   |

### ■ Details

Ready-to-connect 3 phase AC motor starter with undervoltage release and emergency stop button.

### ■ Properties

- 3-pole switch (Contactor)
- Switching capacity up to 7,5 kW
- With undervoltage release
- With emergency stop button
- With connection cable, with CEE-Plug
- With splash water proof cover

### ■ Function

The switch is operated via on / off buttons. The emergency stop button switches the machine voltage free. It can only be switched on again after unlocking by turning the button.

### ■ Mounting

The switch is screwed to the machine via mounting lugs (order).

### ■ Specifications

|                              |   |
|------------------------------|---|
| <b>Voltage Ue</b>            | 400 V~  |
| <b>Contactor</b>             | KliBo7,5, 400V~ (Mod. 403657209)                    |
| <b>Coil voltage Uc</b>       | 400V~   |
| <b>Switching capacity</b>    | 7,5 kW 400V~/AC-3                                   |
| <b>Type of actuation</b>     | Mechanically on/off                                 |
| <b>Connection motor side</b> | 1 m Cable H07RN-G 4 G1,5, stripped with cable lugs  |
| <b>Connection mains side</b> | 2 m Cable H07RN-G 4 G1,5 with CEE-Plug 3P+N+E , 16A |
| <b>Housing material</b>      | Polypropylene PP                                    |
| <b>Mounting position</b>     | any   |
| <b>Protection class</b>      | IP54, splash water proof                            |



