



Insert switch Klinger & Born KB-01-L (Kedu KJD17B-C, DKLD DZ-6)

Manufacturer:	Klinger & Born
Type:	40700010
Product no.:	40700010
Weight:	0.100

■ Details

2-pole insert switch with undervoltage release for machines and stationary power tools

■ Replacement for DKLD DZ-6 (note the dimensions)

The switch can be used as a replacement for the switch DKLD DZ-6 (Yue Qing Dongke Electron). Please note the installation dimensions. There are several variations of DKLD DZ-6.

■ Undervoltage release

Due to the undervoltage release (solenoid) the switch triggers on voltage drop (power failure) and has to be switched back on manually. Therefore it won't switch on spontaneously and uncontrollably.

■ Important information for the switch without coil connection

This switch is currently not available ex works. A switch with a bridge will be shipped instead (refer to image at the bottom).

The switch is functionally identical with the switch without coil connection.

■ Specifications

Voltage	230V~
Rated frequency	50Hz
Operating mode	Continuous operation
Operating current Ie	AC-1 Ue:230V 16,0A, AC-3 Ue:230V 14,5A
Pole number	2 (N/O contacts)
Switching frequency	120 operations / hour
Contacts	Positively driven
Type of actuation	Mechanically on/off
Electrical service life	50.000 switching cycles
Ambient temperature	-25°C . +60°C
Protection class	Front side IP54
Mounting position	Any
Housing material	Plastic PA
Installation	Through 2 holes 4 mm
Connection	Flat plug 6.3x0,8 mm
Corresponds to	IEC947-4-1, EN60947, DIN VDE 0660 part 102
Mark of conformity	VDE-mark of conformity, Reg.Nr. 136105



