





## A.C.-insert switch Kedu KJD12-10ZF

Manufacturer:	Kedu
Type:	KJD12-10ZF
Product no.:	KJD12
Weight:	0.100



### ■ Details

2-pole insert switch with zero voltage release for machines and stationary power tools

Due to the zero voltage release, the switch triggers on voltage drop ( power failure ) and has to be switched back on manually. Therefore it won't switch on spontaneously and uncontrollably.

The keypad is covered by a lid with a lock .

### ■ Specifications

Voltage	230V~
Rated frequency	50Hz
Operating mode	Continuous operation
Operating current I <sub>e</sub>	AC-1 U <sub>e</sub> :230V 16.0A, AC-3 U <sub>e</sub> :230V 10A
Pole number	2 (N/O contacts)
Contacts	Positively driven
Type of actuation	Mechanically on/off
Electrical service life	50.000 switching cycles
Protection class	Front side IP54
Mounting position	Any
Installation	Frame
Connection	Flat plug 6.3x0,8 mm
Corresponds to	IEC947-4-1, EN60947, DIN VDE 0630 part 102

### ■ Replacement for KJD22 from Jiangsu Jinfeida Power Tools

There are **Various KJD22** from Jiangsu Jinfeida Power Tools Co., Ltd. this switch is suitable as a **Replacement for KJD22 with 2 N/O contacts**.

Can not be used as a replacement for KJD22 with 2 N/O contacts and a N/C contact.

### ■ Replacement for KJD3-5/240 from MFD

The switch may be suitable as a replacement for KJD3-5 from MFD, which are used in some drilling machines.

**Please note** the dimensions and the connection. The KJD3-5 has a 4,8 mm flat plug, the KJD12 6.3 mm flat plug.



