



Main switch S1 011/HS-F3-D-RG undervoltage release 230V

Manufacturer: Elektra Tailfingen
Type: S1 011/HS-F3-D-RG
Product no.: 134369
Weight: 0.800

■ Details

Emergency stop-main switch for Frontfixing up to 7.5 kW 400V~/AC-3 with zero voltage release


This switch can be remotely triggered for example with an emergency stop-switch (refer to wiring diagram).

■ Properties

- Clear position indicator with 0 and I
- Contact separation by positively-opening contacts
- **With undervoltage release 230V (neutral conductor required)**
- With connecting clamps-cover with warning sign
- In zero position lockable


■ Specifications

Switching element	3-pol., 25A
Coil voltage	230 V AC
Switching capacity AC-3	7.5 kW (EN 60947-3)
Switching capacity AC-23 A/B	11.0 kW (EN 60947-3)
Rated current I_N	25 A
Operating voltage	400V~
Cable inlet	2 x M20
Protection class	IP54, splash water proof



HS165-230V

Durch Entfernen der Verbindung 14-D2 können bauseitige Elemente (Öffner) angeschlossen werden, z.B. Not-Aus-Taster



HS165-400V

