





Insert switch Klinger & Born K100

Manufacturer:	Klinger & Born
Type:	0099.0100
Product no.:	K100
Weight:	0.100



■ Details

Insert switch for machines and stationary power tools.
The switch has a integrated contactor from Klinger & Born KB-04 with 230V or 400V respectively..
Supply not wired. A undervoltage release must be realized with a circuit.

■ Variations

Model nr.	Switching function	Coil voltage	Contactor
K100-230-4S	4 N/O contacts	230 V	KB-04/230/4S
K100-230-3S1Ö	3 N/O contacts, 1 N/C contacts	230 V	KB-04/230/3S1Ö
K100-400-4S	4 N/O contacts	400 V	KB-04/400/4S
K100-400-3S1Ö	3 N/O contacts, 1 N/C contacts	400 V	KB-04/400/3S1Ö

■ Specifications

Contactor-Typ	KB-04
Coil voltage U_c	230-240 V / 400 V, 50 Hz
Current I_{th}	16 A
Switching capacity	3.0 kW 230V~ AC-3 / 4.0 kW 400V~ AC-3
Switching contacts	4 N/O contacts or 3 N/O contacts + 1 N/C contacts
Per standard	IEC947-4-1, VDE0660-102
Connection	Flat plug 6.3 mm