



## Schurter circuit breaker T11-811

|               |          |
|---------------|----------|
| Manufacturer: | Schurter |
| Type:         | T11-811  |
| Product no.:  | T11-811  |
| Weight:       | 0.050    |

### ■ Details

1-pole thermal over current circuit breaker **Without threadneck** (inserted).

### ■ Properties

- Reliable switching behaviour due to spring-loaded snap mechanism
- Uninfluenceable trip-free mechanism
- Is according to the circuit breaker norm EN 60934 (IEC 60934): R-Typ, TO.

**Important: This switch does not have a thread for installation.**

### ■ Replacement for Weber Unimat

Usable as a replacement for Weber Unimat T11-811 (please note the dimensions)

Possibly also usable as a replacement for T11-411 and T11-414  
Please note the dimensions and connections for those switches.  
suitable for Fein angle grinder with T11-414.

### ■ Specifications

|                            |                                               |
|----------------------------|-----------------------------------------------|
| <b>Nominal current</b>     | 1.0 - 16.0 A                                  |
| <b>Nominal voltage</b>     | AC 240 V, DC 48 V                             |
| <b>Protection class</b>    | Operating area IP40, connecting area IP00     |
| <b>Isolation</b>           | Reinforced isolation in the actuation element |
| <b>Ambient temperature</b> | -5.60 °C                                      |
| <b>Switch-off</b>          | Thermal (träge)                               |
| <b>Approval</b>            | VDE, CSA, UL                                  |
| <b>Installation</b>        | Inserted                                      |
| <b>Connection</b>          | Flat plug 6.3 mm                              |

### ■ Typical areas of application

Power tools, household appliances, overcurrent protection with printed circuits, motorstarter.

